

INTRODUCING **ODYSSEY**[®] *Performance* SERIES™

More overall power and longer service life than conventional batteries

Designed to handle the increased use of onboard accessories in today's vehicles, ODYSSEY[®] Performance Series™ batteries combine long service life, high reliability and deep cycle capabilities.

Packed with pure lead power

ODYSSEY Performance Series batteries contain flat plates made of 99.99% pure lead – not lead alloy, like many conventional batteries. Pure lead plates can be made thinner, so we can fit more of them in the battery. More plates mean more plate surface area, which means more power when you need it.



31-800

ODYSSEY Performance Series batteries provide all the reliability of ODYSSEY Extreme Series™ batteries, without the high cold cranking amps (CCA) or reserve capacity (RC) many people may not require.

POWERFUL PERFORMANCE FOR COMMERCIAL TRUCKS



Commercial trucking & Tractor trailers
With today's no-idling laws, big rigs need a battery that can keep everything in the cab running when the engine isn't. ODYSSEY Performance Series batteries can power a range of on-board accessories and still deliver reliable starts.



www.odysseybattery.com

Powered by **EnerSys**[®]
Power/Full Solutions

POWERFUL REASONS TO CHOOSE ODYSSEY® PERFORMANCE SERIES™ BATTERIES

Longer warranty –
4-year full replacement warranty.

Longer service life –
3-10 years of service life.

Longer cycle life –
70% longer cycle life and up to 400 cycles at 80% depth of discharge.

Longer shelf life –
Storable with nothing connected to the terminals for up to 2 years, or down to 12.00V, whichever comes first.

Faster recharge –
100% recharge in 4-6 hours – the highest efficiency of any sealed lead battery.

More flexible mounting –
Non-spillable design allows mounting on any side, in any position (except inverted).

Vibration resistance –
Protection against the high impact shocks and vibration that often cause premature battery failure.

Extreme temperature tolerance –
Operating temperatures from -40°F (-40°C) to 140°F (60°C).

Maintenance free –
No need to add water, ever!

Improved safety –
Classified “non-spillable” by US Department of Transportation – no acid spills.



ODYSSEY® Performance Series™ Batteries

ODYSSEY® Performance Series™ batteries provide all the reliability of ODYSSEY Extreme Series™ batteries, without the high CCA (cold cranking amps) or RC (reserve capacity) many people may not require.



Lead Posts

Polypropylene Case and Cover
for durability and temperature tolerance


99.99% Pure Lead Plates
are extremely thin, so more of them fit inside for more power

Through-the-wall Intercell Connections

Compressed AGM Plate Separators
help enable extreme vibration resistance

Cutaway image is representative, not actual product

31-800



Drawing size is for terminal position reference only

| Model | Voltage | PHCA** (5 sec) | CCA* | HCA | MCA | Nominal Capacity | | Reserve Capacity Minutes | Length inches (mm) | Width inches (mm) | Height inches (mm) | Weight lbs (kg) | Terminal | Torque Specs in-lbs (Nm max) | Internal Resistance (mΩ) | Short Circuit Current |
|---------------|---------|-------------------|------|------|------|------------------|-----------------|-----------------------------|--------------------------|-------------------------|--------------------------|-----------------------|----------------------------|------------------------------------|-----------------------------|-----------------------|
| | | | | | | (20 Hr Rate-Ah) | (10 Hr Rate-Ah) | | | | | | | | | |
| 31-800 | 12 | 1600 | 802 | 1380 | 1188 | 99 | 94 | 188 | 13.0 (330.2) | 6.78 (172.2) | 9.42 (239.8) | 69.0 (31.3) | 3/8-16 Stud or SAE Post | 200 (22.6) | 2.6 | 2600 |

*Cold Start Performance S.A.E. J537 June 82

** Pulse Current



© 2013 EnerSys. All rights reserved.
Trademarks and logos are the property of EnerSys and its affiliates unless otherwise noted.

Publication No: US-PRF-FL-002 – October 2013. Subject to revisions without prior notice. E.&O.E.

**EnerSys
World Headquarters**
2366 Bernville Road
Reading, PA 19605
Tel: +1-610-208-1991
+1-800-538-3627

EnerSys EMEA
EH Europe GmbH
Löwenstrasse 32
Zürich, Switzerland
Tel: +41 (0) 44 215 74 10

EnerSys Asia
152 Beach Road
Gateway East Building #11-03
Singapore 189721
Tel: +65 6508 1780